

		CONRAD OrderNr	
T1	BF998	153029	Dual gate MOSfet. S=21mS.
T2	BFU590G	DARISUS GMBH	4-pin SOT223-4 12V 2W Ft=8GHz (eBay)
D1,2	1N4148	162280	Fast switching diode
D3	1N5929B	1305070	Zener diode 15V / 2W. Polarity and over voltage protection.
ZD1	BZX79-C14 1N5244BTR	12 62 838	Zener diode 14V / 400mW. Over voltage protection. Normally not active.
1x	BNC bus.	1570027	PCB type, 90 degr. For antenna PCB. Fits PCB.
2x	BNC bus	156 48 88 (740 632)	Standard chassis type BNC bus. For splitter.
	2.1mm bus.	733946	"12V PWR" connector in splitter.
F1	PCB fuse holder 5x20mm Fuse 5x20mm	532908 533173 (157 65 02)	This fuse holder version will fit into the splitter PCB. Preferable 0.16 A slow (or 0.2A slow)
Box	Cabinet	541621	Hammond 1590a Screening aluminum die cast box.
	Ferriet-rings Ui=5000	534480	Cheap ferrite ring core Ui=5000, 14.5x26x20mm. (Or ferrite clamp Ui = 3000 – 10000, with a large hole). For noise blocking on coax or power cables.

Miniwhip parts list Ver. 20180501

pa0nhc Sant 20180415 antPCB 20180316-23 Ssplit 20180423 2/3

L1			Wire bridge. If high frequency range must b limited to f.i. 30 Mhz, try 1 to 4.7 uH axial 7x3mm
L2,3,4	Bourns RLB0912 RM5 (Low Ri)	1056022 1056023	10 uH RLB0912-100KL for ULF range down to 5 kHz. else 100 uH RLB0912-101KL for LF range down to 50 kHz.
L2LF, L3LF, L4LF	Bourns RLB0912 RM5 (Low Ri)	1056024	1 mH 200 mA. For extended ULF range to 5 kHz. else Wire bridge for LF range to 50 kHz.
L5	Würth WE- TOF 7427014	1086891	Mantle current choke / balun, with 2x 5t RG174 coax. Ui=800 ferrite ring 28mm x 16mm x 20mm (Conrad.nl) OR A cheaper 25mm ringcore ferrite type N30 Ui=4300 www.box73.de
C1,3	100n FILM	1235240	<u>NO ceramic</u>
C2	47n FILM	1235249	<u>NO ceramic.</u> 47n limits low freq. range to 5kHz. else 1n limits low freq. range to 250 kHz.
C4LF, C7LF, C9LF	2,2uF FILM RM5 7.2x5mm	1569768	<u>NO ceramic</u> 2u2 for extended low frequency range down to 5 kHz. (1235240 0.1 uF if low frequency range limit = 100 kHz).
C8LF	220uF 25V	446108	Ensures 6 db/oct roll-off below 5 kHz.
C5,6	100uF 16V RM2.5 d=6.3mm	443906	
C4,7,8,9, 11,13	10n FILM	1569681	
C12,15	100pF NP0	157 87 02	
C14,16	22p NP0 500V	1589526	
C17	1n FILM	1235230	Or ceramic <u>NP0</u> . NO other cerematic.

		CONRAD OrderNr	Resistors : Metalfilm 0.25W, 2.3x6.5mm (Bend their wires to RM10).
R1,11, 12	47k	1584432	
R2	22k	1584427	
R3	1k	1583972	Limits VHF range to abt. 50MHz / prevents oscillation. Lower its value for VHF reception.
R4	180 Ohm	1584992	
R5	82 Ohm	1584975	
R6,7	2k2	1583718	
R6a	6k8	1583502	Adjuts Ub to ½ Uc.
R8	220 Ohm	1583659	Limits VHF range to abt. 50MHz / prevents oscillation. Lower its value for VHF reception.
R9	(50 1W) Low Li	1583659 1584992	2x220 + 2x180 Ohm 1/4W in parallel (low Li). For lower current consumption : Omit one or two 180 Ohm resistors.
R10	1k		
R13	47 Ohm	1583650	Prevents oscillations.
R14	2k2		Limits VHF range to abt. 50MHz / prevents oscillation. Lower its value for VHF reception.
R16,17, 18	22 MegOhm	1584814	Carbon resistor. If possible use metal film resistors.

Allowable supply range 9.0 Vdc to 14.0 Vdc.

Measured voltages will vary with varying power supply voltage.

Supply : 14Vdc / 128mA (see R9).

R4 = 3.02 V Max input antenna 7Vpp.

R9 = 5.21 V Max splitter output @ 50 Ohms load (200 kHz) : 0.8 Vrms

Freq. Range : 5 kHz to >30MHz.